

QFP Device Test Interface (44 Pins, 0.80mm Pitch) Part No. CLIP 41-1460

Page 1 of 2 Issue 1 10/02/2010

Introduction

This Test Interface is a hand held test clip, designed to probe simultaneously the leads of an assembled IC. Terminated with a 25 way male "D" type connector, the interface makes temporary electrical contact with the leads of the device, in a two step action:

- the interface is positioned over the device to be tested (Lining it up with the body of the device and the leads).
- Once the CLIP has located on the device, by pushing the handle further, the high-performance microprobes will reach the leads of the device and make electrical contact.

Features

- achieves the best combination of reliability, repeatability, serviceability and user-friendliness;
- high contact pressure at probe tip, for repeatable and reliable contact;
- high reliability and long life interchangeable microprobes;
- sweeping action gold plated contacts, for reliable contact and low ohmic resistance of interconnections;
- high current rating (for single channel, in ambient air with 70°F [20°C]): 1.5A
- impact, solvent and temperature resistant plastics, with low friction;
- wide range of operating temperatures (commercial): [0°C to +70°C]
- clear markings on the body, indicating Pin 1 of IC being tested, to prevent probing the wrong way round;
- packaged in a hard wearing, high resistance to damage Polypropylene case with foam insets, the Test Interface can whitstanding high impact in transit.
- case can be used for safe storage when the Test Interface is not in use, and subsequent transport.
- very flexible cable (military quality harnessing) with low friction, high performance TFE TEFLON insulated wires (MIL-W-16878E Type E, UL1213);




© 201


The copyright in this work is vested in Diagnosys Systems. The document is issued in confidence solely for the purpose for which it is supplied. Reproduction in whole or in part or for use for tendering or manufacturing purposes is prohibited except under an agreement with or with the written consent of Diagnosys Systems, and then only on the condition that this notice is included in any such reproduction. Diagnosys has a policy of continuous improvement and reserves the right to change technical specifications at any time without prior notice. Diagnosys does not accept liability for errors or misprints in this document

Joagnosys can provide a full range of test clips to meet individual requirements. Any common device packaging styles can be accommodated, or custom designed clips manufactured, for device pitches of 0.4mm and above

Specification

- It will accommodate a 44 Pin TQFP Device (0.8mm Pitch) LxWxH: 10mm x 10mm x 2-3mm;
- Maximum number of interconnections (channels): 44
- Current rating, with all contacts loaded (maximum continuous current, non inductive): 0.5A /channel;
- Contact resistance (average): 80 m Ω /channel;
- Insulation resistance: $5M\Omega$ Min.
- Volume resistivity of plastic parts : $10^{15} \Omega$ -cm @ 50%RH.
- Fatigue life of probes: Min. 1,000,000 cycles at normal working distance;
- Working distance (normal stroke): 1.3mm;
- Microprobe force at point of contact (normal stroke): 0.3N





Connections Table

IC Pin	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22
Connector 'A' PIn	1	14	2	15	3	16	4	17	5	18	6	19	7	20	8	21	9	22	10	23	11	24
PinPoint Channel	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22
IC Pin	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44
Connector 'B' Pin	1	14	2	15	3	16	4	17	5	18	6	19	7	20	8	21	9	22	10	23	11	24
PinPoint Channel	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46

- 1) All dimensions in mm, unless otherwise specified.
- 2) Pin 1 of IC marked in red on probe body.

Maintenance

The Test Interface Head is maintenance free. The microprobes are self-cleaning. Immersion in water or contact between microprobes and any liquids should be avoided, as this could severely reduce the working life of microprobes.

Contamination is the primary cause of probe contact problems. This is generally caused by flux left as a residue on circuit boards. Other probe contaminants such as dust, fluff, oil and grime can also cause problems in other areas. Light brushing of the tips of the probes with nylon, bristle or soft metal brushes will dislodge most contaminants.

De copyright in this work is vested in Diagnosys Systems. The document is issued in confidence solely for the purpose for which it is supplied. Reproduction in whole or in part or for use for tendering or manufacturing purposes is prohibited except under an agreement with or with the written consent of Diagnosys Systems, and then only on the condition that this notice is included in any such reproduction. Diagnosys has a policy of continuous improvement and reserves the right to change technical specifications at any time without prior notice. Diagnosys does not accept liability for errors or misprints in this